CIRCUIT BREAKER FINDERS

AUTOMATICALLY FINDS BREAKERS AND FUSES ON 120V AC CIRCUITS

- · cULus 1436 Listed
- · Transmitter Triple Function Signal Transmitter, Receptacle Tester & GFCI Trip Test (61-534 only)
- · Receiver Dual Function Breaker Finder and Non-Contact Voltage Tester (61-534 only)
- · Includes transmitter, receiver and battery







Indication

Scan with your smartphone to learn more



Lead Adapter Kit Provides adapters for use in lighting fixtures.



TL-532A Test Lead & Adapter Kit (sold separately)



US LISTED



US LISTED

CIRCUIT BREAKER FINDERS





CIRCUIT BREAKER FINDER SELECTION GUIDE





TRANSMITTER FEATURES	61-534	61-532
CAT Rating (Safety)	CAT II 300V	CAT II 300V
Listing	UL 1436	UL 1436
Line Voltage	Line Powered (120V AC only)	Line Powered (120V AC only)
Supply Frequency	47-63Hz	47-63Hz
Weight	50g (approx.)	50g (approx.)
Pulse Amplitude	18A (approx.) @ 120V	18A (approx.) @ 120V
Pulse Rate	4mS every 17ms (@ 60Hz)	4mS every 17ms (@ 60Hz)
Power Consumption	200mW max. @ 120V AC	200mW max. @ 120V
Operating Temperature	32° - 122°F (O to 50°C)	32° - 122°F (O to 50°C)
GFCI	✓	_
Polarity Indication	✓	_
RECEIVER FEATURES		
Visual and Audible Indicators	✓	✓
Low Battery Indication	✓	✓
Auto Power Off (after 10 mins. of no activity)	✓	✓
Battery Type	9V	9V
Weight	0.2 lbs. (w/o battery)	0.2 lbs. (w/o battery)
Warranty	2-Year*	2-Year*
ACCESSORIES		
Light Socket and 3-prong to 2-prong Adapters, Alligator Clips	TL-532A	TL-532A

P-6050 (5-21) ©2021 IDEAL INDUSTRIES, INC.

Specifications are subject to change without notice.



