

Keyed Selector Switches



Ordering Guide: Keyed Selector Switches

Example:

52SC6AFK1

- Keyed Selector Switch, 30mm
- Chrome, Standard
- 2-Pos, Maintained
- Key removal in left position
- Cam A
- 1 NC

52SC5BEX300

- Keyed Selector Switch, 30mm
- Chrome, Non-standard key
- 3-Pos, Maintained
- Key removal in all positions
- Cam B
- Lock/key number 548CH

Selection	1	2	3	4	5	6	7
Catalog Number	52	S	C	6	A	F	K1

Use the selection information below to build your keyed selector switch catalog number. Please contact your Siemens account manager for further ordering details.

Selection (1)

Class

52 Pushbutton
(Oil Tight)

(2)

Type

S Keyed Selector Switch

(3)

Model

C Chrome

(4)

Style

5 Non-standard Lock/Key¹
6 Standard Lock/Key

Selection (5)

Cam

A 2 Pos: CAM A
B 3 Pos: CAM B
C 3 Pos: CAM C
D 3 Pos: CAM D
E 3 Pos: CAM E
G 3 Pos: CAM G
H 4 Pos: CAM H

Please see page 29 for Cam selection

(6)

Lock Type

2 Position

E Maintained, removal in both positions
F Maintained, removal in left
G Maintained, removal in right
X Spring return from right, lock left

3 Position

E Maintained, removal in all positions
F Maintained, removal in left
G Maintained, removal in right
H Maintained, removal in center
J Maintained, removal in left and right
K Maintained, removal in left and center
M Maintained, removal in right and center
T Spring return from left, lock center
U Spring return from right, lock center
V Spring return from left and right, lock center
W Spring return from left, lock right
Y Spring return from left, lock center and right
Z Spring return from right, lock left and center

4 Position

E Maintained, removal in all positions
F Maintained, removal in left
G Maintained, removal in right

(7)

Optional: Contact Blocks and Mounting Positions

A0 1 NO - 1 NC (1-52BJK)
Mounted on left
A1 1 NO - 1 NC (1-52BJK)
Mounted on right
A2 2 NO - 2 NC (2-52BJK)
Mounted one left and one right
J0 1 NC (1-52BAJ)
Mounted on left
J1 1 NC (1-52BAJ)
Mounted on right
J2 2 NC (2-52BAJ)
Mounted one left & one right
J2K1 2NC - 1 NO (2-52BAJ and 1-52BAK)
Mounted one left (52BAJ) and one right (52BAK)
K0 1 NO (1-52BAK)
Mounted on left
K1 1 NC (1-52BAK)
Mounted on right
K2 2 NC (2-52BAK)
Mounted one left & one right

Additional contact block combination arrangements are available upon request. See contact block table on page 32 for a complete list of contact block offerings.

See table at top of page 34 for contact block position.

¹ Please append X___ to the end of the catalog number to specify which non-standard lock/key to use. For example, append X299 to get lock/key number 549CH.

X298 = 550CH
X299 = 549CH
X300 = 548CH
X301 = 547CH
X302 = 546CH



Stock Product

The listed keyed selector switches are just a selection of stocked product. Please consult your Siemens accountmanager for a complete list of stocked product.

CHROME Keyed Selector Switches, 30mm

Catalog ID	Pos / Funct	Cam	Key Removal	Key Type	Contacts
52SC6AE	2-Pos, Maintained	A-Cam	All	501CH	
52SC6AF	2-Pos, Maintained	A-Cam	Left	501CH	
52SC6AFK1	2-Pos, Maintained	A-Cam	Left	501CH	1NO (left)
52SC6AX	2-Pos, Spring Return From Right	A-Cam	Left	501CH	
52SC6BE	3-Pos, Maintained	B-Cam	All	501CH	
52SC6BH	3-Pos, Maintained	B-Cam	Center	501CH	
52SC6CE	3-Pos, Maintained	C-Cam	All	501CH	
52SC6BV	3-Pos, Spring Return From Left and Right	B-Cam	Center	501CH	
52SC6HG	4-Pos, Maintained	H-Cam	Right	501CH	