

Sub-Miniature - Minuscules



Fig.131



Fig.120

3

Line Ligne	Lamp Shape Forme Lampe	Volts Tension	Amps (A) Watts Puiss. (W)	Lamp Base Culot Lampe	Internal Code Interne	Filament	Avg. Life (Hrs) Vie moy. (Hres)	Average EFC Pied bougie moyen	Approx. Cold Res. Rés. froid approx. (OHMS)	Lumens	MSCP	L.C.L. Inches - (mm) H.C.L. Pouces - (mm)	M.O.L. Inches - (mm) L.H.T.M. Pouces - (mm)	Diam. inches (mm) Pouces (mm)	Fig. # N° Fig.
------------	------------------------	---------------	---------------------------	-----------------------	-----------------------	----------	---------------------------------	-------------------------------	---	--------	------	---	---	-------------------------------	----------------

T -1 3/4 Bulb Lampe T 1- 3/4

355	T-1 3/4	5	0.115A	W2x4.6d Wedge/Poussoir	56	C-2R	40000				0.15	0.4 (10.2)	0.79 (20)		131
356	T-1 3/4	6	0.2A	W2x4.6d Wedge/Poussoir	79	C-2R	1000				0.6	0.4 (10.2)	0.79 (20)		131
357	T-1 3/4	6.3	0.04A	W2x4.6d Wedge/Poussoir	84	C-2V	20000				0.03	0.4 (10.2)	0.79 (20)		131
358	T-1 3/4	6.3	0.15A	W2x4.6d Wedge/Poussoir	16	C-2V	5000				0.34	0.4 (10.2)	0.79 (20)		131
359	T-1 3/4	6.3	0.2A	W2x4.6d Wedge/Poussoir	86	C-2V	20000				0.4	0.4 (10.2)	0.79 (20)		131
360	T-1 3/4	14	0.04A	W2x4.6d Wedge/Poussoir	18	C-2F	5000				0.13	0.4 (10.2)	0.79 (20)		131
361	T-1 3/4	14	0.08A	W2x4.6d Wedge/Poussoir	73	C-2F	15000				0.3	0.4 (10.2)	0.79 (20)		131
362	T-1 3/4	14	0.09A	W2x4.6d Wedge/Poussoir	37	C-2V	2500				0.5	0.4 (10.2)	0.79 (20)		131
363	T-1 3/4	14	0.15A	W2x4.6d Wedge/Poussoir	70	C-2V	100				1.5	0.4 (10.2)	0.79 (20)		131
364	T-1 3/4	14	0.1A	W2x4.6d Wedge/Poussoir	74	C-2V	1000				0.7	0.4 (10.2)	0.79 (20)		131
365	T-1 3/4	24	0.04A	W2x4.6d Wedge/Poussoir	M2341	C-2F	5000				0.28	0.4 (10.2)	0.79 (20)		131
366	T-1 3/4	24	0.05A	W2x4.6d Wedge/Poussoir	2741	C-2F	2000				0.5	0.4 (10.2)	0.79 (20)		131
367	T-1 3/4	28	0.04A	W2x4.6d Wedge/Poussoir	85	C-2F	7000				0.3	0.4 (10.2)	0.79 (20)		131
368	T-1 3/4	28	0.065A	W2x4.6d Wedge/Poussoir	17	C-2F	5000				0.65	0.4 (10.2)	0.79 (20)		131
369	T-1 3/4	1.35	0.06A	Wire Terminal / Cosses de câbles	1728	C-2R	5000				0.01		0.45 (11.4)	0.2 (5.1)	120
370	T-1 3/4	2	0.06A	Wire Terminal / Cosses de câbles	M2119	C-2R	1000				0.02		0.45 (11.4)	0.2 (5.1)	120
371	T-1 3/4	2.5	0.2A	Wire Terminal / Cosses de câbles	1783	C-2R	1000				0.2		0.45 (11.4)	0.2 (5.1)	120
372	T-1 3/4	2.5	0.35A	Wire Terminal / Cosses de câbles	M2169	C-2R	20000				0.21		0.45 (11.4)	0.2 (5.1)	120
373	T-1 3/4	2.5	0.5A	Wire Terminal / Cosses de câbles	58	C-2R	3000				0.5		0.45 (11.4)	0.2 (5.1)	120
374	T-1 3/4	2.7	0.06A	Wire Terminal / Cosses de câbles	1738	C-2R	6000				0.04		0.45 (11.4)	0.2 (5.1)	120
375	T-1 3/4	3	0.03A	Wire Terminal / Cosses de câbles	M2156	C-2R	1800				0.02		0.45 (11.4)	0.2 (5.1)	120
376	T-1 3/4	3	0.15A	Wire Terminal / Cosses de câbles	M2158	C-2R	20000				0.003		0.45 (11.4)	0.2 (5.1)	120
377	T-1 3/4	3	0.35A	Wire Terminal / Cosses de câbles	8847	C-2R	10000				0.3		0.45 (11.4)	0.2 (5.1)	120
378	T-1 3/4	3	0.3A	Wire Terminal / Cosses de câbles	M2129	C-2R	1500				0.34		0.45 (11.4)	0.2 (5.1)	120
379	T-1 3/4	3.2	0.16A	Wire Terminal / Cosses de câbles	21	C-2R	3000				0.2		0.45 (11.4)	0.2 (5.1)	120
380	T-1 3/4	4.5	0.12A	Wire Terminal / Cosses de câbles	M2171	C-2F	25000				0.05		0.45 (11.4)	0.2 (5.1)	120
381	T-1 3/4	5	0.017A	Wire Terminal / Cosses de câbles	3950	C-2R	2000				0.018		0.45 (11.4)	0.2 (5.1)	120