Branch Breakers Selection for P1

Selection Guide

1. Select breaker type.
2. Select required amperage.
3. Select number of poles.
4. Select branch breaker catalog numbers.
5. Select ground bus and filler plates. (See replacement parts & accessories on page 5 & 6.)

BL Branch Breakers – 10,000A IR

Amp Rating	1-Pole 120/240V	2-Pole 120/240V	2-Pole 240V	3-Pole 240V
15	B115	B215	B215R	B315
20	B120	B220	B220R	B320
25	B125	B225	B225R	B325
30	B130	B230	B230R	B330
40	B140	B240	B240R	B340
50	B150	B250	B250R	B350
60	B160	B260	B260R	B360
70	B170	B270	B270R	B370
80	–	B280	B280R	B380
90	–	B290	B290R	B390
100	–	B2100	B2100R	B3100

BLH Branch Breakers – 22,000A IR

Amp Rating	1-Pole 120/240V	2-Pole 120/240V	3-Pole 240V
15	B115H	B215H	B315H
20	B120H	B220H	B320H
25	B125H	B225H	B325H
30	B130H	B230H	B330H
40	B140H	B240H	B340H
50	B150H	B250H	B350H
60	B160H	B260H	B360H
70	B170H	B270H	B370H
80	–	B280H	B380H
90	–	B290H	B390H
100	–	B2100H	B3100H

HBL Branch Breakers – 65,000A IR

Amp Rating	1-Pole 120/240V	2-Pole 120/240V	3-Pole 240V
15	B115HH	B215HH	B315HH
20	B120HH	B220HH	B320HH
30	B130HH	B230HH	B330HH
40	B140HH	B240HH	B340HH
50	B150HH	B250HH	B350HH
60	–	B260HH	B360HH
70	–	B270HH	B370HH
80	–	B280HH	B380HH
90	–	B290HH	B390HH
100	–	B2100HH	B3100HH

BQD6 Branch Breakers – 10,000A IR Max

Amp Rating	1-Pole 347V	2-Pole 600Y/347V	3-Pole 600Y/347V
15	BQD6115	BQD6215	BQD6315
20	BQD6120	BQD6220	BQD6320
25	BQD6125	BQD6225	BQD6325
30	BQD6130	BQD6230	BQD6330
35	BQD6135	BQD6235	BQD6335
40	BQD6140	BQD6240	BQD6340
45	BQD6145	BQD6245	BQD6345
50	BQD6150	BQD6250	BQD6350
60	BQD6160	BQD6260	BQD6360
70	BQD6170	BQD6270	BQD6370

For detailed circuit breaker information please consult Section #6.

SIEMENS

Molded Case Circuit Breakers

BQD/CQD Type Circuit Breakers Product Bulletin

- UL Listed
- Compact Size
- Single Handle
- Glass Polyester Housing
- Common Trip
- Quick-make Quick-break Trip free Mechanism
- 1, 2 or 3 Pole Units
- UL Listed Field Addable Accessories

Bulletin SIB2.8-1B

Toggle Full Screen | Close | REV | FWD