

Type CBM Bolt-On Loadcentres

Combination (Main Circuit Breaker) Single & Three Phase Copper Bus

Single Phase 120/240VAC Type 1 (Indoor) Loadcentres

- ◆ CSA Certified only (Not UL Approved)
- ◆ Utilize Type BAB, QBHW, QBA, DNBA, or QBGF circuit breakers as branch circuit breakers.

Product Selection

Table 39. Single Phase 3 Wire 120/240VAC Copper Bus Loadcentres

Maximum Ampere Rating	Main Breaker Rating	Catalogue Number	Max. No. 1" Spaces	Max. No. 1/2" Spaces	Cover Style	Dimensions (Inches / mm)			Wire Size Range for Main CU/AL
						H	W	D	
125	100	CBM118CU ①	18	36	Flush/Surface	27 / 685.8	14-1/4 / 361.9	3-3/4 / 95.3	#8 - #1 Cu / #8 - 1/0 Al
125	100	CBM130CU ①	30	60	Flush/Surface	34-1/8 / 866.8	14-1/4 / 361.9	3-3/4 / 95.3	#8 - #1 Cu / #8 - 1/0 Al
125	100	CBM142CU ①	42	84	Flush/Surface	39 / 990.6	14-1/4 / 361.9	3-3/4 / 95.3	#8 - #1 Cu / #8 - 1/0 Al
225	200	CBM218CU ②	18	36	Flush/Surface	34-1/8 / 866.8	14-1/4 / 361.9	3-3/4 / 95.3	#4 - 4/0
225	200	CBM230CU ②	30	60	Flush/Surface	39 / 990.6	14-1/4 / 361.9	3-3/4 / 95.3	#4 - 4/0

Three Phase 240VAC Type 1 (Indoor) Loadcentres

- ◆ CSA Certified only (Not UL Approved)
- ◆ Utilize Type BAB, QBHW, QBA, DNBA, or QBGF circuit breakers as branch circuit breakers.

Product Selection

Table 40. Three Phase 4 Wire 240VAC Maximum Copper Bus Loadcentres

Maximum Ampere Rating	Main Breaker Rating	Catalogue Number	Max. No. 1" Spaces	Max. No. 1/2" Spaces	Cover Style	Dimensions (Inches / mm)			Wire Size Range for Main CU/AL
						H	W	D	
125	100	3CBM118CU ③	18	36	Flush/Surface	27 / 685.8	14-1/4 / 361.9	3-3/4 / 95.3	#8 - #1 Cu / #8 - 1/0 Al
125	100	3CBM130CU ③	30	60	Flush/Surface	34-1/8 / 866.8	14-1/4 / 361.9	3-3/4 / 95.3	#8 - #1 Cu / #8 - 1/0 Al
125	100	3CBM142CU ③	42	84	Flush/Surface	39 / 990.6	14-1/4 / 361.9	3-3/4 / 95.3	#8 - #1 Cu / #8 - 1/0 Al
225	200	3CBM230CU ④	30	60	Flush/Surface	39 / 990.6	14-1/4 / 361.9	3-3/4 / 95.3	#4 - 4/0

① BAB2100 Main circuit breaker factory installed.

② ED2200 Main circuit breaker factory installed.

③ BAB3100H Main circuit breaker factory installed.

④ ED3200 Main circuit breaker factory installed.