# **Axial Lead & Cartridge Fuses** 3AG > Slo-Blo® Fuse > 313/315 Series

# 313/315 Series Lead-Free 3AG, Slo-Blo® Fuse





#### **Agency Approvals**

Agency Agency File Number		Ampere Range		
(l)	E10480	0.010A - 10A**		
<b>(</b>	29862	0.010A - 10A**/15A**		
<b>71</b>	E10480	10A - 30A		
	313 Series (Cartridge): NBK060618-E10480A NBK060618-E10480C	1-5A 6.25- 10A**		
Ē	315 Series (Leaded): NBK060618-E10480B NBK060618-E10480D	1-5A 6.25-10A**		
	SU05001-6004 SU05001-5007 SU05001-5008 SU05001-5009	2.25-2.5A 2.8A - 3.2A 4A - 6.3A 7A-8A		
€	N/A	0.010A - 10A**/15A**		

<sup>\*\*</sup> See note under Electrical Characteristics by item

#### **Description**

The 3AG Slo-Blo® fuse solves a broad range of application requirements while offering reliable performance and costeffective circuit protection.

The fuse catalog number with the suffix "ID" instantly identifies itself upon opening by showing a discoloration of its glass body. Guesswork and time consuming circuit testing are eliminated. This unique design offers the same quality performance characteristics as the standard 3AG Slo-Blo® Fuse design.

#### **Features**

- In accordance with UL Standard 248-14
- Available in cartridge and axial lead format and with various forming dimensions
- RoHS compliant and Lead-free

## **Applications**

Used as supplementary protection in appliance or utilization equipment to provide individual protection for components or internal circuits.

## **Additional Information**



Datasheet 313 Series



315 Series



Resources 313 Series



Resources 315 Series



Samples 313 Series



Samples 315 Series



# **Electrical Characteristics by Series**

% of Ampere Rating	Ampere Rating	Opening Time
100%	10mA – 30A	4 hours, Minimum
135%	10mA – 30A	1 hour, Maximum
200%	10mA – 15A	5 sec., Min.,30 sec., Max
20076	20A – 30A	5 sec., Min.,60 sec Max

For recommended fuse accessories for this product series, see 'Recommended Accessories' section.

# **Axial Lead & Cartridge Fuses** 3AG > Slo-Blo® Fuse > 313/315 Series

# **Electrical Characteristic Specifications by Item**

Amp Code	Ampere	Voltage Rating (V)	Interrupting Rating	Nominal Cold Resistance (Ohms)	Nominal Melting I²t (A² sec)	Agency Approvals					
	Rating (A)					(UL)	<b>(</b>		<i>A</i>	PS	Œ
0.01	0.01	250		4300.0000	0.000121	X	Х				X
0.031	0.031	250		430.0000	0.00303	X	×				Х
0.04	0.04	250		300.0000	0.00630	X	×				Х
0.062	0.062	250		120.0000	0.0210	X	×				Х
0.1	0.1	250		43.0000	0.0850	Х	×				Х
0.125	0.125	250		30.0000	0.152	Х	×				X
0.15	0.15	250		20.0000	0.270	Х	×				Х
0.175	0.175	250		8.6700	0.177	Х	Х				X
0.187	0.187	250		8.0100	0.230	Х	×				Х
0.2	0.2	250	35A@250Vac	6.5900	0.270	Х	Х				X
0.25	0.25	250	10KA@125Vac	4.2700	0.385	Х	×				Х
0.3	0.3	250		3.1350	0.730	X	Х				Х
0.375	0.375	250		2.0950	1.23	X	Х				Х
0.4	0.4	250		1.8750	1.35	Х	Х				Х
0.5*	0.5	250		1.2600	2.55	Х	×				Х
0.6	0.6	250		0.9120	4.00	X	×				Х
0.7	0.7	250		0.7000	5.90	Х	×				Х
0.75	0.75	250		0.6215	7.16	X	×				Х
0.8	0.8	250		0.5540	8.00	Х	×				Х
1.0*	1	250		0.3750	14.0	X	×			×	X
1.2	1.2	250		0.2780	21.5	Х	×			×	Х
1.25	1.25	250		0.2600	24.0	Х	Х			×	X
1.5*	1.5	250		0.1910	38.0	Х	Х			×	X
1.6	1.6	250		0.1710	49.6	Х	Х			×	X
1.8	1.8	250	1004@050\/	0.1410	92.0	Х	X			×	Х
2.0*	2	250	100A@250Vac	0.1169	77.0	Х	X			×	X
2.25	2.25	250	10KA@125Vac	0.0968	121	Х	X	X		X	Х
2.5	2.5	250		0.0811	199	Х	X	X		X	Х
2.8	2.8	250		0.0675	269	Х	X	X		X	Х
3.*	3	250		0.0593	200	Х	X	X		X	Х
3.2	3.2	250	1	0.0529	209	Х	Х	Х		Х	Х
4.0*	4	250		0.0311	76.1	X	X	Х		Х	Х
5.0*	5	250		0.0214	276	Х	Х	Х		Х	Х
6.25*	6.25	250	2004@250\/-	0.0154	388	Х	X	Х		Х	Х
6.3	6.3	250	200A@250Vac	0.0154	388	Х	Х	Х		Х	Х
7.0*	7	250	10KA@125Vac	0.0128	547	Х	Х	Х		Х	X
8.0*	8	250		0.0111	701	X	Х	Х		Х	Х
10.0**	10	250		0.0083	1285	Х	Х			Х	Х
10.0*	10	32		0.0083	1285				X		
12.0	12	32		0.0065	1200				Х		
15.0**	15	125	1	0.0050	2650		Х		X	Х	Х
15.0	15	32	300A@32Vac	0.0050	2650				X		
20.0	20	32	1	0.0022	9560				X		
25.0	25	32		0.0017	16500				X		
30.0	30	32		0.0012	26900				X		

<sup>\*</sup> For 313series, these ratings available with an indicating option. Add the "ID" designation to the series number i.e. 313.500ID.

\*\* The 10A and 15A ratings are ratings are designed for special voltage requirement. For 10A, it is available as 250Vac rated and the part number is 0313010.MX250P; For 15A, it is available as 125Vac rated and the part number is 0315015.MX125P.

# Axial Lead & Cartridge Fuses 3AG > Slo-Blo® Fuse > 313/315 Series

#### **Product Characteristics**

Materials	Body: Glass Cap: Nickel-plated brass Leads: Tin-plated Copper
Terminal Strength	MIL-STD-202, Method 211, Test Condition A
Solderability	MIL-STD-202 method 208
Product Marking	Cap1: Brand logo, current and voltage ratings Cap2: Series and agency approval marks


Operating Temperature	-55°C to +125°C
Thermal Shock	MIL-STD-202, Method 107, Test Condition B: (5 cycles -65°C to +125°C)
Vibration	MIL-STD-202, Method 201
Humidity	MILSTD-202, Method 103, Test Condition A: High RH (95%) and Elevated temperature (40°C) for 240 hours
Salt Spray	MIL- STD-202, Method 101, Test Condition B

## **Dimensions**

#### **313 000P Series 315 000P Series** (cartridge) (axial leaded) 6.35±0.3 (.25") 6.985±0.3 (.275")32.72±1.12 **Axial Lead Diameter: Axial Lead Length:** 0.81±0.05 (.032") for (0.01A - 15A) 38.1±3.15 (1.50") TYP. **Axial Lead Material:** 1.02±0.06 (.040") for (20A - 30A) Tin-coated copper

Measurements displayed in millimeters (inches)

## **Part Numbering System**



## **Recommended Accessories**

Accessory Type	Series	Description	Max Application Voltage	Max Application Amperage
Holder	<u>155100</u>	Twist-Lock In-Line Fuseholder	32	20
	342	Traditional Panel Mount Fuseholder	250	20
	346	Panel Mount Flip-Top Shock-Safe Fuseholder	250	15
	<u>345</u>	Shock-Safe Fuseholder with PC Mount, Solder Mount and Panel Mount options	250	16
Block	<u>354</u>	Low Profile OMNI-BLOK® Fuse Block	600	30
DIOCK	<u>359</u>	359 High Current Screw Terminal Fuse Block		30
Clin	<u>122</u>	High Current Traditional PC Board Fuse Clip	1000	30
Clip	<u>101</u>	Rivet/Eyelet Type Fuse Clip	1000	15

#### Notes:

- Do not use in applications above rating.
- 2. Please refer to fuseholder data sheet for specific re-rating information.
- 3. Please contact factory for applications greater than the max voltage and amperage shown.