# Plug Fuses: G/GP/TD/GW/GTL/GT/GSL

#### UL/CSA LISTED POWER FUSES



Mersen Plug Fuses are for industrial and residential applications. Standard non-time delay fuses are for receptacle and lighting circuits. Standard time delay fuses are for motor loads. For Canadian requirements, a type "P" fuse is used for non-motor loads and type "D" fuses are used for electric heating and cycling loads circuits. Both fuses have low melting-point temperature elements. Low-Temp time delay plug fuses have thermal sensitivity are also for cycling loads and motor circuits. Type "S" plug fuses are time delay and tamper-resistant.

### CATALOG NUMBERS (AMPS)

| Catalog Number       |                       |                  |                                   |                              |                               |                                |
|----------------------|-----------------------|------------------|-----------------------------------|------------------------------|-------------------------------|--------------------------------|
| Edison Base          |                       |                  |                                   |                              |                               | Туре S                         |
| Non-Time<br>Delay UL | Non-Time<br>Delay CSA | Time-delay<br>UL | "P" Type<br>Non-time<br>Delay CSA | Low-Temp<br>Time-delay<br>UL | "D" Type<br>Time-delay<br>CSA | Rejection*<br>Time-delay<br>UL |
| GW3                  | G3                    | -                | -                                 | -                            | -                             | -                              |
| GW6                  | G6                    | -                | -                                 | -                            | -                             | -                              |
| GW10                 | G10                   | -                | -                                 | -                            | -                             | -                              |
| GW15                 | -                     | GTL15            | GP15                              | GT15                         | TD15                          | GSL15                          |
| GW20                 | -                     | GTL20            | GP20                              | GT20                         | TD20                          | GSL20                          |
| GW25                 | -                     | GTL25            | GP25                              | GT25                         | TD25                          | GSL25                          |
| GW30                 | -                     | GTL30            | GP30                              | GT30                         | TD30                          | GSL30                          |

FR15 Rejector Rings available

FRW Rejection removal tool available to remove FR15 \*Must be used with an SAG adaptor to fit an Edison base fuse holder.

### RATINGS:

- **Volts:** 125VAC
- **Amps:** 3 to 30A
- IR: 10kA I.R. AC
- Choice of Edison Base, Types "P," "D," or "S"

#### APPROVALS:

- UL Listed Guide JEFV, File E76208
- CSA Certified Class 142301, File 15525



## TYPE S PLUG FUSE ADAPTORS

Type S adaptors screw into the Edison base and allow Type S fuses to be installed. Type S adaptors prevent the wrong ampere size fuse from being used.



 Cat.No./Rating
 Fuse Range - Amps

 SAG3-2/10
 1-8/10 - 3-2/10

 SAG6-1/4
 3-1/2 - 6-1/4

 SAG15
 7 - 15

 SAG20
 20

 SAG30
 25 - 30

