



STANDBY GENERATORS



Automatic Transfer Switch

The transfer switch is the brain behind the standby generator. Installed next to your circuit breaker, its job is to sense when the power goes out and automatically switch the generator on and manage the homes backup power.

Briggs & Stratton has been providing reliable engine power for more than 100 years. Trust the proven power experts at Briggs & Stratton for complete peace of mind.





SPECIFICATIONS

Model Number	01918	071075	071047	071076	071055	071038	071045	071069	071046	071036	071058
Frequency	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz	60Hz
Circuits	10	10	16	16	Whole House	Whole House	Whole House	Whole House	Whole House	Whole House	Whole House
Amps	50A	50A	100A	100A	100A	200A	100A	150A	200A	200A	2X200A
Transfer Switch Utility Breaker	-	-	-	-	-	-	100A	150A	200A	200A	2X200A
Transfer Switch Gen Breaker	-	-	-	-	-	-	100A	100A	100A	200A	200A
Enclose Type	NEMA 3R	NEMA 3R	NEMA 3R	NEMA 3R	NEMA 3R	NEMA 3R	NEMA 3R	NEMA 3R	NEMA 3R	NEMA 3R	NEMA 3R
Includes 2ft ATS (distribution) Whip	No	Yes, 50A	No	Yes, 100A	No	No	No	No	No	No	No
Voltage (P-N/P-P)	120/240	120/240	120/240	120/240	120/240	120/240	120/240	120/240	120/240	120/240	120/240
Phase	Single	Single	Single	Single	Single	Single	Single	Single	Single	Single	Single
Load Transition Type (Automatic)	Break Before Make	Break Before Make	Open Transition	Open Transition	Open Transition	Open Transition	Open Transition, Service Rated	Open Transition, Service Rated	Open Transition, Service Rated	Open Transition, Service Rated	Open Transition, Service Rated
UL Rating	1008	1008	1008	1008	1008	1008	1008	1008	1008	1008	1008
Withstand Rating (RMS Symmetrical Amperes)	5,000	5,000	5,000	5,000	5,000	10,000	22,000	25,000	25,000	25,000	25,000
Lug Range	#14 - #6	#14 - #6	1/0 - #14	1/0 - #14	1/0 - #14	250MCM - #6	1/0 - #14	250MCM - #6	250MCM - #6	250MCM - #6	250MCM - #6
Length	21.2"	25"	24.1"	27.5"	16.0"	30.1"	24.1"	30.1"	30.1"	30.1"	37.0"
Width	14.5"	14.5"	14.0"	14.0"	12.0"	15.9"	14.0"	15.9"	15.9"	15.9"	24.0"
Height	5.4"	5.4"	6.1"	6.1"	6.1"	7.1"	6.1"	7.1"	7.1"	7.1"	7.0"

FEATURES & BENEFITS

Automatic Power

Automatically signals the generator to start and manages backup power when power goes out.

Flexible Placement

Weather Resistant NEMA 3R rated for maximum protection against dirt, rain, sleet and snow. Suitable for indoor and outdoor installation.

Air Conditioning Control Module (ACCM)

Patented technology manages the load of 1 or 2 air conditioners while keeping household appliances powered (excludes 50 amp models).

OPERATIONS & SETTINGS

Utility voltage drop-out	<70%
Time for generator to start	6 second factory set
Engine warm-up delay	20 or 50 seconds
Utility voltage pickup	>80%
Re-transfer delay	10 seconds
Cool-down timer	60 seconds
Exerciser (controlled by generator)	20 minutes every 7 days

