



Bolt-on mini-power center (copper-wound transformer and loadcenter chassis standard) catalog number information

kVA	Style number	Full capacity taps FCBN	Dimensions in inches (mm) ①			Weight Lb (kg)	Frame	Main circuit breaker ②		Feeder breakers max. number ④ ⑤			
			Height	Width	Depth			Primary ③	Secondary	Single-pole	Two-pole	Three-pole	Max. amp
Single-phase													
480 V to 120/240 V													
3	P48G11S0318CUB	2 at -5%	36.14 (918.0)	12.56 (319.0)	9.66 (245.4)	110 (50)	FR307	EHD2015	BAB2015	18	9	—	12
5	P48G11S0518CUB	2 at -5%	36.14 (918.0)	12.56 (319.0)	9.66 (245.4)	110 (50)	FR307	EHD2020	BAB2025	18	9	—	20
7.5	P48G11S0718CUB	2 at -5%	36.14 (918.0)	12.56 (319.0)	9.66 (245.4)	110 (50)	FR307	EHD2030	BAB2030	18	9	—	30
10	P48G11S1024CUB	2 at -5%	43.91 (1115.3)	14.97 (380.2)	11.82 (300.2)	215 (98)	FR309	EHD2040	BAB2050	24	12	—	40
15	P48G11S1530CUB	2 at -5%	43.37 (1101.6)	20.41 (518.4)	14.58 (370.3)	385 (175)	FR310	EHD2060	BAB2070	30	15	—	60
25	P48G11S2530CUB	2 at -5%	43.37 (1101.6)	20.41 (518.4)	14.58 (370.3)	385 (175)	FR310	EHD2100	BAB2125	30	15	—	100
600 V to 120/240 V													
3	P60G11S0318CUB	2 at -5%	36.14 (918.0)	12.56 (319.0)	9.66 (245.4)	110 (50)	FR307	FDB2015	BAB2015	18	9	—	12
5	P60G11S0518CUB	2 at -5%	36.14 (918.0)	12.56 (319.0)	9.66 (245.4)	110 (50)	FR307	FDB2020	BAB2025	18	9	—	20
7.5	P60G11S0718CUB	2 at -5%	36.14 (918.0)	12.56 (319.0)	9.66 (245.4)	110 (50)	FR307	FDB2030	BAB2030	18	9	—	30
10	P60G11S1024CUB	2 at -5%	43.91 (1115.3)	14.97 (380.2)	11.82 (300.2)	215 (98)	FR309	FDB2040	BAB2050	24	12	—	40
15	P60G11S1530CUB	2 at -5%	43.37 (1101.6)	20.41 (518.4)	14.58 (370.3)	385 (175)	FR310	FDB2060	BAB2070	30	15	—	60
25	P60G11S2530CUB	2 at -5%	43.37 (1101.6)	20.41 (518.4)	14.58 (370.3)	385 (175)	FR310	FDB2100	BAB2125	30	15	—	100
Three-phase													
480 V to 208Y/120 V													
15	P48G28T1518CUB	2 at -5%	34.27 (870.5)	31.50 (800.1)	9.35 (237.5)	320 (145)	FR289B	EHD3040	BAB3050H	18	9	6	40
22.5	P48G28T2124CUB	2 at -5%	40.01 (1016.3)	32.63 (828.8)	13.62 (345.9)	635 (288)	FR291B	EHD3070	BAB3070H	24	12	6	60
30	P48G28T3024CUB	2 at -5%	40.01 (1016.3)	32.63 (828.8)	13.62 (345.9)	635 (288)	FR291B	EHD3090	BAB3100H	24	12	8	80
600 V to 208Y/120 V													
15	P60G28T1518CUB	2 at -5%	34.27 (870.5)	31.50 (800.1)	9.35 (237.5)	320 (145)	FR289B	FDB3030	BAB3050H	18	9	6	40
22.5	P60G28T2124CUB	2 at -5%	40.01 (1016.3)	32.63 (828.8)	13.62 (345.9)	635 (288)	FR291B	FDB3050	BAB3070H	24	12	6	60
30	P60G28T3024CUB	2 at -5%	40.01 (1016.3)	32.63 (828.8)	13.62 (345.9)	635 (288)	FR291B	FDB3070	BAB3100H	24	12	8	80

- ① Not for construction purposes.
- ② Main breakers fixed only. No substitutes for ampere rating.
- ③ Optional AIC rated main breakers available. See table on page 3.
- ④ Combinations can be selected.
- ⑤ Feeder breakers not included. Use Eaton's Type BAB family.