## SIEMENS

## Data sheet

## 6ES7134-6HD01-0BA1



SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XU/I 2-WIRE STANDARD, PACKING UNIT: 1 PIECE, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT, +/-0,3%

General information	
Product type designation	AI 4x U/I 2-wire
HW functional status	From FS02
Firmware version	
FW update possible	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC03
Product function	
● I&M data	Yes; I&M0 to I&M3
<ul> <li>Isochronous mode</li> </ul>	No
<ul> <li>Measuring range scalable</li> </ul>	No
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V14 / -
STEP 7 configurable/integrated from version	V5.6 and higher
PCS 7 configurable/integrated from version	V8.1 SP1
PROFIBUS from GSD version/GSD revision	One GSD file each, Revision 3 and 5 and higher
PROFINET from GSD version/GSD revision	GSDML V2.3
Operating mode	
Oversampling	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
<ul> <li>Short-circuit protection</li> </ul>	Yes
<ul> <li>Output current, max.</li> </ul>	20 mA; max. 50 mA per channel for a duration < 10 s
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	
Address space per module	

<ul> <li>Address space per module, max.</li> </ul>	8 byte; + 1 byte for QI information
Hardware configuration	
Automatic encoding	Yes
Mechanical coding element	Yes
Type of mechanical coding element	Туре А
Selection of BaseUnit for connection variants	.,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,
2-wire connection	BU type A0, A1
Analog inputs	
Number of analog inputs	4; Differential inputs
permissible input voltage for voltage input (destruction	30 V
limit), max.	
permissible input current for current input (destruction	50 mA
limit), max.	
Cycle time (all channels), min.	Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels)
Input ranges (rated values), voltages	(depending on the parameterization of the active channels)
• 0 to +10 V	Yes: 15 bit
— Input resistance (0 to 10 V)	120 kΩ
• 1 V to 5 V	Yes: 15 bit
— Input resistance (1 V to 5 V)	120 kΩ
• -10 V to +10 V	Yes; 16 bit incl. sign
— Input resistance (-10 V to +10 V)	120 kΩ
• -5 V to +5 V	Yes; 16 bit incl. sign
<ul> <li>Input resistance (-5 V to +5 V)</li> </ul>	120 kΩ
Input ranges (rated values), currents	
• 0 to 20 mA	Yes; 15 bit
<ul> <li>Input resistance (0 to 20 mA)</li> </ul>	100 Ω; + approx. 0.7 V diode forward voltage
• 4 mA to 20 mA	Yes; 15 bit
— Input resistance (4 mA to 20 mA)	100 Ω; + approx. 0.7 V diode forward voltage
Cable length	
<ul> <li>shielded, max.</li> </ul>	1 000 m; 200 m for voltage measurement
Analog value generation for the inputs	
Measurement principle	integrating (Sigma-Delta)
Integration and conversion time/resolution per channel	
<ul> <li>Resolution with overrange (bit including sign), max.</li> </ul>	16 bit
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> </ul>	Yes
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference</li> </ul>	
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> </ul>	Yes 16.6 / 50 / 60 Hz
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> </ul>	Yes
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> </ul>	Yes 16.6 / 50 / 60 Hz
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> </ul> Smoothing of measured values <ul> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes Yes 650 Ω
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes 550 Ω No
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul> Encoder Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> Errors/accuracies Linearity error (relative to input range), (+/-)	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes Yes 650 Ω
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes 650 Ω No
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul> Encoder Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> Errors/accuracies Linearity error (relative to input range), (+/-)	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes 650 Ω No 0.01 % 0.005 %/K
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB 0.05 %
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul> Encoder Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> Errors/accuracies Linearity error (relative to input range), (+/-) <ul> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB 0.05 %
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul> Encoder Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> Errors/accuracies Linearity error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range <ul> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB 0.05 %
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul> Encoder Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range <ul> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB 0.05 %
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB 0.05 % 0.5 % 0.5 %
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB 0.05 % 0.5 % 0.5 % 0.3 % 0.3 %
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 =</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB 0.05 % 0.05 % 0.3 % 0.3 % 0.3 % 0.3 %
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul> Encoder Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range <ul> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Exercer limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB 0.05 % 0.5 % 0.5 % 0.3 % 0.3 %
<ul> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Conversion time (per channel)</li> <li>Smoothing of measured values</li> <li>Number of smoothing levels</li> <li>parameterizable</li> </ul> Encoder Connection of signal encoders <ul> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range <ul> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 =</li> </ul>	Yes 16.6 / 50 / 60 Hz 180 / 60 / 50 ms 4; None; 4/8/16 times Yes Yes Yes 650 Ω No 0.01 % 0.005 %/K 50 dB 0.05 % 0.05 % 0.3 % 0.3 % 0.3 % 0.3 %

Common mode interference, min.	90 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes
Limit value alarm	No
Diagnoses	
<ul> <li>Monitoring the supply voltage</li> </ul>	Yes
Wire-break	Yes; at 4 to 20 mA
Short-circuit	Yes; with 1 to 5 V or 2-wire mode: Short-circuit of the encoder supply to ground or of an input to the encoder supply
Group error	Yes
Overflow/underflow	Yes
Diagnostics indication LED	
<ul> <li>Monitoring of the supply voltage (PWR-LED)</li> </ul>	Yes; green LED
<ul> <li>Channel status display</li> </ul>	Yes; green LED
<ul> <li>for channel diagnostics</li> </ul>	No
for module diagnostics	Yes; green/red LED
Potential separation	
Potential separation channels	
<ul> <li>between the channels</li> </ul>	Yes; channel group-specific between 2-wire current input group and voltage input group
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>between the channels and the power supply of the electronics</li> </ul>	Yes; only for voltage inputs
Permissible potential difference	
between the inputs (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Standards, approvals, certificates	
Suitable for applications according to AMS 2750 Suitable for applications according to CQI-9	Yes; Declaration of Conformity, see online support entry 109757262 Yes
Ambient conditions	103
Ambient temperature during operation	20 °C; < 0 °C as of EC02
horizontal installation, min.	-30 °C; < 0 °C as of FS02
horizontal installation, max.	60 °C
vertical installation, min.	-30 °C; < 0 °C as of FS02 50 °C
<ul> <li>vertical installation, max.</li> <li>Altitude during operation relating to sea level</li> </ul>	50 0
Installation altitude above sea level, max.	E 000 m: Destrictions for installation altitudes > 2 000 m ass manual
	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Dimensions Width	15 mm
Dimensions Width Height	15 mm 73 mm
Dimensions Width Height Depth	15 mm
Dimensions Width Height Depth Weights	15 mm 73 mm 58 mm
Dimensions Width Height Depth	15 mm 73 mm