## **SIEMENS**

## **Data sheet**

## 6ES7134-6GD01-0BA1



SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XI 2-/4-WIRE STANDARD, PACKING UNIT: 1 PIECE, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT, +/-0,3%

General information	
Product type designation	Al 4xl 2-/4-wire ST
HW functional status	From FS02
Firmware version	
FW update possible	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC03
Product function	
● I&M data	Yes; I&M0 to I&M3
<ul> <li>Isochronous mode</li> </ul>	No
Measuring range scalable	No
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V14 / -
<ul> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.6 and higher
<ul> <li>PCS 7 configurable/integrated from version</li> </ul>	V8.1 SP1
<ul> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	One GSD file each, Revision 3 and 5 and higher
PROFINET from GSD version/GSD revision	GSDML V2.3
Operating mode	
<ul> <li>Oversampling</li> </ul>	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
Short-circuit protection	Yes
<ul> <li>Output current, max.</li> </ul>	20 mA; max. 50 mA per channel for a duration < 10 s
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	
Address space per module	
<ul> <li>Address space per module, max.</li> </ul>	8 byte; + 1 byte for QI information

Hardware configuration	
Automatic encoding	Yes
Mechanical coding element	Yes
Type of mechanical coding element	Type A
Selection of BaseUnit for connection variants	
2-wire connection	BU type A0, A1
4-wire connection	BU type A0, A1
Analog inputs	
Number of analog inputs	4; Differential inputs
permissible input current for current input (destruction limit), max.	50 mA
Cycle time (all channels), min.	Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels)
Input ranges (rated values), currents	
• 0 to 20 mA	Yes; 16 bit incl. sign
<ul><li>— Input resistance (0 to 20 mA)</li></ul>	100 $\Omega$ ; + approx. 0.7 V diode forward voltage in 2-wire operation
• -20 mA to +20 mA	Yes
<ul><li>— Input resistance (-20 mA to +20 mA)</li></ul>	100 Ω
• 4 mA to 20 mA	Yes; 15 bit
— Input resistance (4 mA to 20 mA)	100 Ω; + approx. 0.7 V diode forward voltage in 2-wire operation
Cable length	4.000
• shielded, max.	1 000 m
Analog value generation for the inputs	
Measurement principle	integrating (Sigma-Delta)
Integration and conversion time/resolution per channel	16 hit
Resolution with overrange (bit including sign), max.	16 bit Yes
Integration time, parameterizable     Interference voltage suppression for interference	16.6 / 50 / 60 Hz
<ul> <li>Interference voltage suppression for interference frequency f1 in Hz</li> </ul>	10.0 / 30 / 60 HZ
Conversion time (per channel)	180 / 60 / 50 ms
Smoothing of measured values	
<ul> <li>Number of smoothing levels</li> </ul>	4; None; 4/8/16 times
<ul> <li>parameterizable</li> </ul>	Yes
Encoder	
Connection of signal encoders	
- for voltage measurement	
<ul> <li>for voltage measurement</li> </ul>	No
<ul><li>for voltage measurement</li><li>for current measurement as 2-wire transducer</li></ul>	No Yes
-	
<ul> <li>for current measurement as 2-wire transducer</li> <li>— Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul>	Yes
for current measurement as 2-wire transducer     — Burden of 2-wire transmitter, max.     for current measurement as 4-wire transducer  Errors/accuracies	Yes 650 Ω Yes
for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.     for current measurement as 4-wire transducer      Errors/accuracies  Linearity error (relative to input range), (+/-)	Yes 650 Ω Yes 0.01 %
for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.         • for current measurement as 4-wire transducer          Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)	Yes 650 Ω Yes 0.01 % 0.005 %/K
for current measurement as 2-wire transducer     — Burden of 2-wire transmitter, max.     for current measurement as 4-wire transducer      Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.	Yes $650~\Omega$ Yes $0.01~\%$ $0.005~\%/K$ $50~dB; Applies to up to \pm 5~V overvoltage in other channels$
for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.         • for current measurement as 4-wire transducer          Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	Yes 650 Ω Yes 0.01 % 0.005 %/K
for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.         • for current measurement as 4-wire transducer          Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range	Yes 650 Ω Yes  0.01 % 0.005 %/K  50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %
for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.         • for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range         • Current, relative to input range, (+/-)	Yes $650~\Omega$ Yes $0.01~\%$ $0.005~\%/K$ $50~dB; Applies to up to \pm 5~V overvoltage in other channels$
for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.         • for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range         • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)	Yes 650 $\Omega$ Yes $0.01 \%$ 0.005 %/K $50 \text{ dB; Applies to up to } \pm 5 \text{ V overvoltage in other channels}$ 0.05 % $0.5 \%$
for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.         • for current measurement as 4-wire transducer          Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range         • Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)          • Current, relative to input range, (+/-)	Yes 650 $\Omega$ Yes $0.01 \%$ $0.005 \%/K$ $50 dB; Applies to up to \pm 5 \ V overvoltage in other channels 0.05 \% 0.5 \%$
<ul> <li>for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.     </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference-mode interference / with interference voltage</li> </ul>	Yes 650 $\Omega$ Yes $0.01 \%$ $0.005 \%/K$ $50 dB; Applies to up to \pm 5 \ V overvoltage in other channels 0.05 \% 0.5 \%$
<ul> <li>for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.     </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference-mode interference / with interference voltage suppression / minimum</li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB
<ul> <li>for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.     </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference roughly interference voltage suppression / minimum</li> <li>Common mode voltage, max.</li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB  10 V
<ul> <li>for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range         <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression / minimum</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB
<ul> <li>for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.     </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression / minimum</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> <li>Interrupts/diagnostics/status information</li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB  10 V 90 dB
<ul> <li>for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.     </li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression / minimum</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB  10 V
<ul> <li>for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interespies-mode interference / with interference voltage suppression / minimum</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms</li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB 10 V 90 dB
<ul> <li>for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interespications / minimum</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms</li> <li>Diagnostic alarm</li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB  10 V 90 dB  Yes
<ul> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies         <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> </ul> </li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range         <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Basic error limit (operational limit at 25 °C)         <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression / minimum         <ul> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> </ul> </li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Limit value alarm</li> </ul> </li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB 10 V 90 dB
<ul> <li>for current measurement as 2-wire transducer         — Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Current, relative to input range, (+/-)</li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = intermediate interference / with interference voltage suppression / minimum</li> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms</li> <li>Diagnostic alarm</li> <li>Limit value alarm</li> <li>Diagnoses</li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB  10 V 90 dB  Yes  Yes No
<ul> <li>for current measurement as 2-wire transducer         <ul> <li>Burden of 2-wire transmitter, max.</li> <li>for current measurement as 4-wire transducer</li> </ul> </li> <li>Errors/accuracies         <ul> <li>Linearity error (relative to input range), (+/-)</li> <li>Temperature error (relative to input range), (+/-)</li> <li>Crosstalk between the inputs, min.</li> </ul> </li> <li>Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)</li> <li>Operational error limit in overall temperature range         <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Basic error limit (operational limit at 25 °C)         <ul> <li>Current, relative to input range, (+/-)</li> </ul> </li> <li>Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression / minimum         <ul> <li>Common mode voltage, max.</li> <li>Common mode interference, min.</li> </ul> </li> <li>Interrupts/diagnostics/status information</li> <li>Diagnostics function</li> <li>Alarms         <ul> <li>Diagnostic alarm</li> <li>Limit value alarm</li> </ul> </li> </ul>	Yes 650 Ω Yes  0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %  0.5 %  0.3 %  rference frequency 70 dB  10 V 90 dB  Yes

Short-circuit	Yes; 2-wire mode: Short-circuit of the encoder supply to ground or of an input to the encoder supply
Group error	Yes
<ul> <li>Overflow/underflow</li> </ul>	Yes
Diagnostics indication LED	
<ul> <li>Monitoring of the supply voltage (PWR-LED)</li> </ul>	Yes; green LED
<ul> <li>Channel status display</li> </ul>	Yes; green LED
<ul> <li>for channel diagnostics</li> </ul>	No
<ul> <li>for module diagnostics</li> </ul>	Yes; green/red LED
Potential separation	
Potential separation channels	
• between the channels	Yes; channel group-specific between 2-wire current input group and 4-wire voltage input group
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>between the channels and the power supply of the electronics</li> </ul>	Yes; only for 4-wire transducer
Permissible potential difference	
between the inputs (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions	
Ambient temperature during operation	
<ul> <li>horizontal installation, min.</li> </ul>	-30 °C; < 0 °C as of FS02
<ul> <li>horizontal installation, max.</li> </ul>	60 °C
<ul> <li>vertical installation, min.</li> </ul>	-30 °C; < 0 °C as of FS02
vertical installation, max.	50 °C
Altitude during operation relating to sea level	
<ul> <li>Installation altitude above sea level, max.</li> </ul>	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	31 g

last modified:

9/7/2023