

Eaton PDG33P0400FNNN

Catalog Number: PDG33P0400FNNN

Eaton Power Defense molded case circuit breaker, Globally Rated, Frame 3, Three Pole, 400A, 100kA/480V, Frame Only, No Terminals

Photo is representative

General specifications

Product Name	Catalog Number
Eaton Power Defense molded case circuit breaker	PDG33P0400FNNN
	UPC
	786689217532
Product Length/Depth	Product Height
4.294 in	10.12 in
Product Width	Product Weight
5.46 in	10.56 lb
Compliances	Certifications
RoHS Compliant	IEC 60947-2
	UL 489
	CCC Marked
	CSA



Delivery program

Amperage Rating

400 A

Circuit breaker frame type

Complete breaker

Frame

3

Number of poles

Three-pole

General information

Circuit breaker type

PD3 Global

Class

Class A

Series

Power defense

Technical data - Electrical

Rated operational current

400 A

Voltage rating

600 Vac

Voltage rating - max

600 V

Technical data - Mechanical - Terminals

Terminals

No Terminals

Technical information

Interrupt rating

100 kAIC at 480 Vac

Interrupt rating range

200 kAIC @240V (UL)

65 kAIC @600V (UL/CSA)

200 kAIC Icu/ 150 kAIC Ics/ 440 kAIC Icm @240V (IEC)

100 kAIC Icu/ 70 kAIC Ics/ 220 kAIC Icm @380-415V (IEC)

100 kAIC Icu/ 50 kAIC Ics/ 220 kAIC Icm @440V (IEC)

85 kAIC Icu/ 40 kAIC Ics/ 187 kAIC Icm @480V Brazil (IEC)

40 kAIC Icu/ 25 kAIC Ics/ 84 kAIC Icm @525V South Africa (IEC)

20 kAIC Icu/ 10 kAIC Ics/ 42 kAIC Icm @690V (IEC)

42 kAIC Icu @250 Vdc

Rating plug

No

Short-circuit breaking capacity

100 kAIC at 480 Vac

Resources

Brochures

StrandAble terminals product aid

Power Defense molded case circuit breaker selection poster

Power Defense technical selling booklet

Certification reports

PDG3 45-400A CB report

EU Declaration of Conformity - Power Defense molded case circuit breakers

PDG3 CSA certification 100-400a

PDG3 UL authorization 100-400a

PDG3 CSA certification 250-600a

PDG3 UL authorization 250-600a TMTU

PDG3B 450A-600A CB report

Installation instructions

Power Defense Frame 3 interphase barrier - IL012229EN H03

Power Defense Frame 1-2-3-4 IP door barrier assembly instructions - IL012278EN

Power Defense Frame 3 multi wire connector kit -

PDG3X3(2)(4)TA4006W and PDG3X3(2)(4)TA4003W instructions- IL012247EN H01

Power Defense Frame 3 shunt trip UVR instructions - IL012140EN

Power Defense Frame 3 terminal cover assembly instructions - IL012281EN

Power Defense Frame 3 trip unit replacement instructions - IL012157EN

Power Defense Frame 3 multi-tap terminal kit Cat Num

PDG3X3(2)(4)TA6006W Instructions - IL012248EN

Power Defense Frame 3 box terminal installation instructions - IL012299EN

Power Defense Frame 3 reverse feed connector kit Cat Num

PDG3X3(2)(4)TA630RF instructions - IL012253EN

Power Defense Frame 3 screw terminal_end cap kit, 400A, 3 pole – IL012262EN

Power Defense Frame 3 interphase barriers 3-pole - IL012229EN H01

Power Defense Frame 4 reverse feed connector kit instructions for PDG4X3(2)(4)TA800RF instructions - IL012254EN

Power Defense Frame 3 reverse feed connector kit Cat Num

PDG3X3(2)(4)TA400HRF instructions - IL012252EN

Power Defense Frame 3 Aux, Alarm, ST and UVR Animated Instructions.rh

Power Defense Frame 3 Direct Rotary Handle Assy With Interlock Version Instructions (IL012139EN).pdf

Power Defense Frame 4 shunt trip UVR instructions - IL012129EN

Power Defense Frame 4 locking devices and handle block instructions -
IL012151EN

Power Defense Frame 3 plug-in adapter installation instructions -
IL012311EN

Power Defense Frame 3 screw terminal end cap kit 600A, 3 pole -
IL012264EN

Power Defense Frame 3 terminal kit Cat Num PDG3X3(2)(4)TA400RF
instructions - IL012251EN

Power Defense Frame 3 adapter kit installation instructions LZM3 to PD3
- IL012227EN

Power Defense Frame 3 extendable shaft rotary handle mech -
IL012112EN

Power Defense Frame 3 finger protection assembly installation
instructions - IL012279EN

Power Defense Frame 3 terminal spreader assembly instructions -
IL012301EN

Power Defense Frame 2/3/4/5/6 voltage neutral sensor module wiring
instructions – IL012316EN

Power Defense Frame 3 Breaker Instructions (IL012107EN).pdf

Power Defense Frame 3 handle mech direct rotary handle instructions -
IL012111EN

Power Defense Frame 3 locking devices and handle block instructions -
IL012150EN

Power Defense Frame 3 rear connection installation instructions -
IL012300EN

Power Defense Frame 3 multi-tap terminal kit Cat Num
PDG3X3(2)(4)TA6006WSW instructions - IL012250EN

Installation videos

Power Defense Frame 3 Handle Mech Variable Depth Rotary Handle
Animated Instructions.rh

Power Defense Frame 3 Shunt Trip_UVR Animated Instructions.pdf.rh

Power Defense Frame 3 Handle Mech Direct Rotary Handle Animated
Instructions.rh

Power Defense Frame 3 Locking Devices and Handle Block Animated
Instructions.pdf.rh

Power Defense Frame 3 trip unit replacement animated instructions.rh

Multimedia

Power Defense Frame 3 Variable Depth Rotary Handle Mechanism
Installation How-To Video

Power Defense Frame 5 Trip Unit How-To Video

Power Defense Frame 6 Trip Unit How-To Video

Power Defense Frame 2 Variable Depth Rotary Handle Mechanism

[Installation How-To Video](#)

[Power Defense molded case circuit breakers](#)

[Eaton Power Defense for superior arc flash safety](#)

[Power Defense Breakers](#)

Specifications and datasheets

[Eaton Specification Sheet - PDG33P0400FNNN](#)

Time/current curves

[Power Defense time current curve Frame 3 - PD3](#)

White papers

[Intelligent power starts with accurate, actionable data](#)

[Intelligent circuit protection yields space savings](#)

[Implementation of arc flash mitigating solutions at industrial manufacturing facilities](#)

[Safer by design: arc energy reduction techniques](#)

[Single and double break MCCB performance revisited](#)

[Molded case and low-voltage power circuit breaker health](#)

[Making a better machine](#)



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)