

Enclosed Modular IEC Motor Starter Packages

3RE4 Non-Reversing Starter, 3-Pole (both 1-Ph, 3-Ph), Large NEMA 1 Enclosure

Selection **NEW**



Ordering Information

- ▶ Can be converted to a motor starter by installing an overload relay (see page 5).
- ▶ NEMA 1 Enclosure.
- ▶ 110/120 VAC 50/60 Hz coils.
- ▶ For accessories, see page 6 – 7.
- ▶ For replacement parts, see page 7.
- ▶ For dimensions, see page 8.
- ▶ For wiring diagrams, see page 9 – 10.

Non-Reversing Starter, 3-Pole (for both 1-Phase and 3-Phase), Large Enclosure

Catalogue Number	Control Transformer	Operator Devices	Unused Aux Contacts		Contactor Ref Number	Frame Size	Maximum HP Rating						
			NO	NC			1-Phase			3-Phase			
							115V	208V	230V	208V	230V	460V	575V
3RE4161-5BA30-0YP0	600/120V, 45VA	Start-Stop push buttons, red On pilot light	0	0	15	S00	—	—	—	—	—	—	5
3RE4161-5BA30-0YB4	208/120V, 45VA	Start-Stop push buttons, red On pilot light	0	0	15	S00	—	0.5	—	1.5	—	—	—
3RE4161-5BA30-0YC1	240/120V, 45VA	Start-Stop push buttons, red On pilot light	0	0	15	S00	—	—	0.75	—	2	—	—
3RE4161-5BA30-0YC7	480/120V, 45VA	Start-Stop push buttons, red On pilot light	0	0	15	S00	—	—	—	—	—	3	—
3RE4161-5BA30-0YP1	600/120V, 45VA	HOA Selector Switch, red On pilot light	1	0	15	S00	—	—	—	—	—	—	5
3RE4161-5BA30-0YG1	208/120V, 45VA	HOA Selector Switch, red On pilot light	1	0	15	S00	—	0.5	—	1.5	—	—	—
3RE4161-5BA30-0YG7	240/120V, 45VA	HOA Selector Switch, red On pilot light	1	0	15	S00	—	—	0.75	—	2	—	—
3RE4161-5BA30-0YH4	480/120V, 45VA	HOA Selector Switch, red On pilot light	1	0	15	S00	—	—	—	—	—	3	—
3RE4161-5BA30-0YY0	None	None	1	0	15	S00	0.25	0.5	0.75	1.5	2	3	5
3RE4161-7BA30-0YP0	600/120V, 45VA	Start-Stop push buttons, red On pilot light	0	0	17	S00	—	—	—	—	—	—	10
3RE4161-7BA30-0YB4	208/120V, 45VA	Start-Stop push buttons, red On pilot light	0	0	17	S00	—	1.5	—	3	—	—	—
3RE4161-7BA30-0YC1	240/120V, 45VA	Start-Stop push buttons, red On pilot light	0	0	17	S00	—	—	2	—	3	—	—
3RE4161-7BA30-0YC7	480/120V, 45VA	Start-Stop push buttons, red On pilot light	0	0	17	S00	—	—	—	—	—	7.5	—
3RE4161-7BA30-0YP1	600/120V, 45VA	HOA Selector Switch, red On pilot light	1	0	17	S00	—	—	—	—	—	—	10
3RE4161-7BA30-0YG1	208/120V, 45VA	HOA Selector Switch, red On pilot light	1	0	17	S00	—	1.5	—	3	—	—	—
3RE4161-7BA30-0YG7	240/120V, 45VA	HOA Selector Switch, red On pilot light	1	0	17	S00	—	—	2	—	3	—	—
3RE4161-7BA30-0YH4	480/120V, 45VA	HOA Selector Switch, red On pilot light	1	0	17	S00	—	—	—	—	—	7.5	—
3RE4161-7BA30-0YY0	None	None	1	0	17	S00	0.5	1.5	2	3	3	7.5	10
3RE4162-5BA30-0YP0	600/120V, 75VA	Start-Stop push buttons, red On pilot light	0	1	25	S0	—	—	—	—	—	—	15
3RE4162-5BA30-0YP1	600/120V, 75VA	HOA Selector Switch, red On pilot light	1	1	25	S0	—	—	—	—	—	—	15
3RE4162-8BA30-0YP0	600/120V, 75VA	Start-Stop push buttons, red On pilot light	0	1	28	S0	—	—	—	—	—	—	25
3RE4162-8BA30-0YB4	208/120V, 75VA	Start-Stop push buttons, red On pilot light	0	1	28	S0	—	5	—	10	—	—	—
3RE4162-8BA30-0YC1	240/120V, 75VA	Start-Stop push buttons, red On pilot light	0	1	28	S0	—	—	5	—	10	—	—
3RE4162-8BA30-0YC7	480/120V, 75VA	Start-Stop push buttons, red On pilot light	0	1	28	S0	—	—	—	—	—	25	—
3RE4162-8BA30-0YP1	600/120V, 75VA	HOA Selector Switch, red On pilot light	1	1	28	S0	—	—	—	—	—	—	25
3RE4162-8BA30-0YG1	208/120V, 75VA	HOA Selector Switch, red On pilot light	1	1	28	S0	—	5	—	10	—	—	—
3RE4162-8BA30-0YG7	240/120V, 75VA	HOA Selector Switch, red On pilot light	1	1	28	S0	—	—	5	—	10	—	—
3RE4162-8BA30-0YH4	480/120V, 75VA	HOA Selector Switch, red On pilot light	1	1	28	S0	—	—	—	—	—	25	—
3RE4162-8BA30-0YY0	None	None	1	1	28	S0	3	5	5	10	10	25	25