
Floor Boxes

Flush Round Single or Multi-Service

Non-Metallic Concrete Floor Box

Dimensions Inches (mm)





B C	PFB1
Min. Depth of Pour	3.00" (76.2)
Capacity	100 cubic inches prior to cutting level to floor (19.5 cubic inches per inch of depth).
Dimensions - A	6.00" (152.4)
Dimensions - B	7.08" (179.8)
Dimensions - C	6.69" (169.9)
Dimensions - D	5.38" (136.5)
Hubs	(2) 1.0" and (2) 3/4" conduit hubs
Concrete Cover Included	✓
Closure/Reducer Plugs	(2) 1" plugs close off 1" hubs or reduce 1" to 3/4"

Note: UL File Number E92074. CSA File Number LR18416.









Description	Numbers
Adapter	PFBA1A

Required for all applications.



PFBT1A **Low Voltage Divider** Required for use with catalog number PFB1 when used in multi-service applications. Accepts Hubbell standard duplex receptacles or 15A Twist-Lock®

duplex receptacles (HBL4700 series).



"Y" Adapter PFBYA1

34 in. "Y" adapter to feed parallel runs of ¾ in. conduit.

Flush Round Covers and Flanges

Multi-Service Cover and Flange Assemblies

Includes floor box cover with duplex flaps, (2) 1/2 in. dia. low voltage feed through holes and matching carpet flange. 6.25 in. Diameter



Brass



(2) 34" plugs close off 34" hubs or reduce 34" to 1/2"

Brown Non-Metallic





Ivorv Non-Metallic

PFBCGYA



Gray Non-Metallic

PFBCBLA

Black Non-Metallic

S3325

Single Service Covers

Brass Aluminum 3.88 in. Dia.



S3925

Duplex Flap





Duplex Screw



21/8" x 3/4" Combination



Combination

S2925 SA2925

21/8" Single Receptacle

S3525

2%" Single Receptacle

21/8" Single Receptacle (Terrazzo Floor)

Metal Carpet Flange

Use with single service covers for carpet applications. 6.25 in. Diameter



Brass



Alum. Finish

Adapter Ring

Use with single service covers for tile applications.



Brass



Aluminum

Furniture Feed Plate

Unpainted plate with 1 in. threaded opening. PFBP1



Steel

One Piece Brass Cover and Carpet Flange

6.25 in. Diameter



Duplex



SF2525*

21/8" x 3/4" Combination



SF2725*

21/8" x 1" Combination



SF2925*

21/8" Single Receptacle

^{*} Catalog Number S5016 adapter ring is required for mounting SF series covers covers onto PFBA1A.





