



















Round Extension and Fixture Boxes	4.75 inches	Outside Diameter 5.50 inches	6.38 inches	Color
<p><b>Extension Box with Open Base</b> For mounting on 3.25 in. (83.00) or 4 in. (102.00) round or square conduit boxes or other recessed outlets. Cover takes any device with mounting screw centers of 2.75 in. (69.85), 3.5 in. (89.00) and 4.06 in. (103.00). Can be used as a pull or junction box when used with <b>HBL5736IV</b> (blank cover).</p> 	<p><b>HBL5737IV</b> <b>HBL5737W</b> A: 1.02" (26.00) B: 4.75" (120.65)</p> 	<p><b>HBL5737AIV</b> <b>HBL5737AW</b> A: 1.02" (26.00) B: 5.50" (140.00)</p> 	<p><b>HBL5739AIV</b> — A: 1.02" (26.00) B: 6.38" (162.01)</p> 	Ivory White
<p><b>Fixture Box with Solid Base</b> To hang fixtures. Cover takes any device with mounting screw centers of 2.75 in. (69.85), 3.5 in. (89.00) and 4.06 in. (103.00). Can be used as a pull or junction box when used with <b>HBL5736IV</b> (blank cover).</p> 	<p><b>HBL5738IV</b> <b>HBL5738W</b> A: 1.02" (26.00) B: 4.75" (120.65)</p> 	<p><b>HBL5738AIV</b> <b>HBL5738AW</b> A: 1.02" (26.00) B: 5.50" (140.00)</p> 	<p><b>HBL5739IV</b> <b>HBL5739W</b> A: 1.02" (26.00) B: 6.38" (162.01)</p> 	Ivory White
Other Round Boxes and Covers	Catalog Numbers			Color
<p><b>Outlet Box</b> For devices with mounting screw centers of 1.47 in. (37.00), 1.63 in. (41.00), 1.69 in. (44.00) or 1.84 in. (46.00).</p> 		<p><b>HBL5733IV</b> A: 1.02" (26.00) B: 3.00" (76.00)</p>		Ivory
<p><b>Blank Cover</b> For use with <b>HBL5733IV</b>. Has ½ in. trade size KO in center.</p> 		<p><b>HBL5731IV</b> A: .24" (6.10) B: 2.40" (60.96)</p>		Ivory
<p><b>Blank Cover</b> For use with <b>HBL5735IV, HBL5737IV/W, HBL5737AIV/W, HBL5739AIV, HBL5738IV/W, HBL5738AIV/W</b> and <b>HBL5739IV/W</b>. Has ½ in. trade size KO in center.</p> 		<p><b>HBL5736IV</b> <b>HBL5736W</b> A: .38" (9.75) B: 4.19" (106.30)</p>		Ivory White
<p><b>Fanbox with Solid Base</b> Cover accepts fan bracket with mounting centers of 3.2 in. (81.00). Rated for fans and fixtures up to 50 lbs.</p> 		<p><b>HBL5738AIV</b> <b>HBL5738AFW</b> A: 1.02" (26.00) B: 4.76" (120.90)</p>		Ivory White
<p><b>Retrofit Box for Fire Alarm Detectors</b> For installing round alarm sensors.</p> 		<p><b>HBL5739AABIV</b> A: 1.62" (41.15) B: 6.50" (165.10)</p>		Ivory

