

# Miniature - Miniatures



Fig.62



Fig.65

Line Ligne	Lamp Shape Forme lampe	Volts Tension	Amps (A) Watts Puiss. (W)	Lamp Base Culot Lampe	Internal Code Interne	Filament	Couleur Couleur	Avg. Life (Hrs) Vie moy. (Hrs)	Lumens	MSCP	L.C.L. Inches - (mm) H.C.L. Pouces - (mm)	M.O.L. Inches - (mm) L.H.T.M. Pouces - (mm)	Diam. inches (mm) Pouces (mm)	Fig. # N° Fig.
---------------	---------------------------------	------------------	---------------------------------	--------------------------------	-----------------------------	----------	--------------------	---	--------	------	--	--	-------------------------------------	-------------------------

## T-3 1/4 Bulb Lampe T-3 1/4

552	T-3 1/4	15.5	0.24A	BA9s	1881	C-2F		500	2,2		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
553	T-3 1/4	18	0.15A	BA9s	1826	C-2V		250	1,8		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
554	T-3 1/4	24	0.17	BA9s	1818	C-2V		250		3.3	5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
555	T-3 1/4	24	0.06A	BA9s	1437	C-2F		20	0,9		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
556	T-3 1/4	24	2W	BA9s	3797	C-2V		3000			0.551 (14)	0.984 (25)	13/32 (10.3)	62
557	T-3 1/4	28	0.022	BA9s	1843	C-2F		3000		0.2	5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
558	T-3 1/4	28	0.17	BA9s	1864	C-2F		1500		3	5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
559	T-3 1/4	28	0.17	BA9s	313	C-2F		500		3.5	5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
560	T-3 1/4	28	0.17	BA9s	313R	C-2F	Red Rouge	500		3.5	5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
561	T-3 1/4	28	0.17	BA9s	313B	C-2F	Blue Bleu	500		3.5	5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
562	T-3 1/4	28	0.04A	BA9s	1819	C-2F		1000	0,34		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
563	T-3 1/4	28	0.07A	BA9s	1829	C-2F		1000	1		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
564	T-3 1/4	28	0.08A	BA9s	757	C-2F		7500	0,62		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
565	T-3 1/4	28	0.1A	BA9s	1820	C-2F		1000	1,6		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
566	T-3 1/4	28	0.2A	BA9s	1873	C-2F		7000	3		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
567	T-3 1/4	30	2W	BA9s	SP-125	C-2F		3000			5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
568	T-3 1/4	36	0.1A	BA9s	1822	C-2V		1000	2,5		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
569	T-3 1/4	37.5	0.05A	BA9s	1828	C-2F		3000	0,65		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
570	T-3 1/4	48	2W	BA9s	SP-120	CC-2F		3000			5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
571	T-3 1/4	55	0.05A	BA9s	1835	CC-2F		5000	1,1		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	62
572	T-3 1/4	60	2W	BA9s	SP-121	C-5		3000			5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	65
573	T-3 1/4	125	0.025 (3W)	BA9s	967	C-7A		5000	0,36		5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	65
574	T-3 1/4	125	6W	BA9s	SP-114			5000				1 3/16 (30)	13/32 (10.3)	65
575	T-3 1/4	130	2.6W	BA9s	949	C-7A		3000			5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	65
576	T-3 1/4	130	2.6W	BA9s	B3013	C-5A		1500			13/16 (20.6)	1 3/16 (30)	13/32 (10.3)	65
577	T-3 1/4	130	3W	BA9s	SP-105	C-7A		10000			0.59 (15)	0.984 (25)	13/32 (10.3)	65
578	T-3 1/4	160	3W	BA9s	SP-122	C-7A		3000			5/8 (15.9)	1 3/16 (30)	13/32 (10.3)	65