

Miniature - Miniatures



Fig.3



Fig.2



Fig.4



Fig.5



Fig.8



Fig.6



Fig.7

Line Ligne	Lamp Shape Forme lampe	Volts Tension	Amps (A) Watts Puiss. (W)	Lamp Base Culot Lampe	Internal Code Interne	Filament	Couleur Couleur	Avg Life (Hrs) Vie moy. (Hres)	Lumens	MSCP	L.C.L. Inches - (mm) H.C.L. Pouces - (mm)	M.O.L. Inches - (mm) L.H.T.M. Pouces - (mm)	Diam. Inches (mm) Pouces (mm)	Fig. # N° Fig.
---------------	---------------------------------	------------------	---------------------------------	--------------------------------	-----------------------------	----------	--------------------	---	--------	------	--	--	-------------------------------------	-------------------------

B-6 Bulb Lampe B-6

26	B-6	6	0.51	BA15s	1317	C-6		100		3.4	1 1/8 (28.6)	1 3/4 (44.4)	3/4 (19.8)	3
27	B-6	6.5	1.78A	BA15d	210	C-6		100		15	1 1/16 (27)	1 3/4 (44.4)	3/4 (19.8)	2
28	B-6	12.8	0.94A	BA15d	1004	C-6		200		15	1 1/16 (27)	1 3/4 (44.4)	3/4 (19.8)	2
29	B-6	12.8	0.94A	BA15s	1003	C-6		200		15	1 1/16 (27)	1 3/4 (44.4)	3/4 (19.8)	3
30	B-6	12.8	1A	BA15d	104	C-6		500		12	1 1/16 (27)	1 3/4 (44.4)	3/4 (19.8)	2
31	B-6	12.8	1A	BA15s	105	C-6		500		12	1 1/16 (27)	1 3/4 (44.4)	3/4 (19.8)	3
32	B-6	28	0.52	BA15s	1309	2C-2R		300		15	1 1/16 (27)	1 3/4 (44.4)	3/4 (19.8)	4
33	B-6	28	0.56	BA15s	1308	CC-8		2000		16	1 1/16 (27)	1 3/4 (44.4)	3/4 (19.8)	5

C-7 Bulb Lampe C-7

34	C-7	125	10W	BA15d	10C7-125V/DC	C-7A		3000	60		1 1/4 (32)	2 3/16 (55)	7/8 (22)	8
35	C-7	125	7W	BA15d	7C7-125V/DC	C-7A		3000	40		1 1/4 (32)	2 3/16 (55)	7/8 (22)	8
36	C-7	130	10W	BA15d	10C7-130V/DC	C-7A		3000	60		1 1/4 (32)	2 3/16 (55)	7/8 (22)	8
37	C-7	250	10W	BA15d	10C7-250V/DC	C-7A		3000	60		1 1/4 (32)	2 3/16 (55)	7/8 (22)	8
38	C-7	250	7W	BA15d	7C7-250V/DC	C-7A		3000	40		1 1/4 (32)	2 3/16 (55)	7/8 (22)	8
39	C-7	120	7W	E12	7C7-120V/CAND/CB	C-7A	Cr.Blue Bleu	3000			1 1/2 (38)	2 1/8 (54)	7/8 (22)	6
40	C-7	120	7W	E12	7C7-120V/CAND/CG	C-7A	Cr.Green Vert	3000			1 1/2 (38)	2 1/8 (54)	7/8 (22)	6
41	C-7	120	7W	E12	7C7-120V/CAND/TA	C-7A	Tr. Amber Ambré	3000			1 1/2 (38)	2 1/8 (54)	7/8 (22)	7
42	C-7	125	10W	E12	10C7-125V/CC	C-7A		3000	60		1 1/2 (38)	2 1/8 (54)	7/8 (22)	7
43	C-7	125	7W	E12	7C7-125V/CC	C-7A	Clear Claire	3000	40		1 1/2 (38)	2 1/8 (54)	7/8 (22)	7
44	C-7	125	7W	E12	7C7-125V/CW	C-7A	White blanc	3000			1 1/2 (38)	2 1/8 (54)	7/8 (22)	6
45	C-7	130	10W	E12	10C7-130V/CC	C-7A		3000	60		1 1/2 (38)	2 1/8 (54)	7/8 (22)	7
46	C-7	130	7W	E12	7C7-130V/CO	C-7A	Cr. Orange	3000			1 1/2 (38)	2 1/8 (54)	7/8 (22)	6
47	C-7	130	7W	E12	7C7-130V/CR	C-7A	Cr. Red Rouge	3000			1 1/2 (38)	2 1/8 (54)	7/8 (22)	6
48	C-7	130	7W	E12	7C7-130V/CC	C-7A		3000	40		1 1/2 (38)	2 1/8 (54)	7/8 (22)	7
49	C-7	145	7W	E12	7C7-145V/CC	C-7A		3000	40		1 1/2 (38)	2 1/8 (54)	7/8 (22)	7