

**BQD Branch Breakers – 14,000A IR Max. @ 480/277V AC
65,000A IR max. @ 240V AC**

Amp Rating	1-Pole 277V	2-Pole 480Y/277V	3-Pole 480Y/277V
15	BQD115	BQD215	BQD315
20	BQD120	BQD220	BQD320
25	BQD125	BQD225	BQD325
30	BQD130	BQD230	BQD330
35	BQD135	BQD235	BQD335
40	BQD140	BQD240	BQD340
45	BQD145	BQD245	BQD345
50	BQD150	BQD250	BQD350
60	BQD160	BQD260	BQD360
70	BQD170	BQD270	BQD370
80	BQD180	BQD280	BQD380
90	BQD190	BQD290	BQD390
100	BQD1100	BQD2100	BQD3100

GFCI Personnel Protection (5MA)

Breaker Type	Ampere Rating	Catalog Number	Interrupting Ratings (kA) (RMS Symmetrical Amperes)		
			Volts AC		
			120	120/240	240
BLF 1-Pole	15	BF115	10	—	—
	20	BF120	10	—	—
	25	BF125 ■	10	—	—
	30	BF130	10	—	—
BLF 2-Pole	15	BF215	—	10	—
	20	BF220	—	10	—
	30	BF230	—	10	—
	40	BF240 ■	—	10	—
	50	BF250 ■	—	10	—
	60	BF260 ■	—	10	—
BLHF 1-Pole	15	BF115H	22	—	—
	20	BF120H	22	—	—
	30	BF130H ■	22	—	—
BLHF 2-Pole	15	BF215H ■	—	22	—
	20	BF220H ■	—	22	—
	30	BF230H ■	—	22	—
	40	BF240H ■	—	22	—
	50	BF250H ■	—	22	—
	60	BF260H ■	—	22	—

EQF Equipment Protection (30MA)

BLE 1-Pole 120V AC	15	BE115 ■	10	—	—
	20	BE120	10	—	—
	30	BE130	10	—	—
BLE 2-Pole 120/240V AC	15	BE215 ■	—	10	—
	20	BE220	—	10	—
	30	BE230	—	10	—
	40	BE240 ■	—	10	—
	50	BE250 ■	—	10	—
	60	BE260 ■	—	10	—
BLEH 1-Pole	20	BE120H ■	22	—	—
	30	BE130H ■	22	—	—
BLEH 2-Pole	15	BE215H ■	—	22	—
	20	BE220H ■	—	22	—
	30	BE230H ■	—	22	—
	40	BE240H ■	—	22	—
	50	BE250H ■	—	22	—
	60	BE260H ■	—	22	—

■ Built to order. Allow 2-3 weeks for delivery.