
Common Voltage Configurations


The wiring diagrams below illustrate the common voltage configurations for Intermatic surge products. Locate the desired voltage configuration and surge protector part number, and then go to the applicable product page to order the desired item(s).


120 VAC Single Phase


H


AG3000
AG2401C3
IG1240RC3
IG3240RC3
IG3240RC3
IG1300-2T-1C3
IG1300-4T-2C3
IG2240 Series
IG2280 Series














Note: All SPDs protect against surges that travel along the electrical pathway and are not applicable to direct lightning strikes that travel down non-electrical paths. Be sure to have at least a 20 A dual pole breaker(s) to help prevent the circuits from shorting. Type 1 SPDs are normally mounted before panels, which would not include a breaker.

Surge Glossary -

Maximum Continuous Operating Voltage (MCOV): The maximum RMS voltage that may be applied to each mode of a surge protection device. (Listed on the product)

Modes Of Protection: Electrical paths within a system which an SPD offers defense against surge events. Examples of protection include, Line to Neutral (L-N), Line to Ground (L-G), Line to Line (L-L) and Neutral to Ground (N-G). (Listed on the product)

Nominal Discharge Current (In): Peak value of the current through the SPD having a current wave shape of 8/20 where the SPD remains functional after 15 surges. (Listed on the product)

Nominal System Voltage: The voltage level at which a system normally operates. Nominal system voltages include, but are not limited to, 120, 208, 240, 277, 347, 480, 600 VAC. (Listed on the product)

Short Circuit Current Rating (SCCR): The measurement of how much current the electrical system can supply during a fault condition. This value determines where an SPD may be installed. (Listed on the product)

Surge: A sudden and sharp increase of current or voltage within electric circuits.

Surge Protective Device (SPD): A device used to limit a surge on equipment by diverting or limiting it. SPDs were previously known as Transient Voltage Surge Suppressors or secondary surge arresters.

Voltage Protection Rating (VPR): The value assigned by UL which specifies the measured limited voltage value of the SPD. VPR rating is formally known as the "suppressed voltage rating". (Listed on the product)