



## LIGHTING AND PLUG LOAD POWER PACK

BZ-200 | [Wattstopper](#)

### FEATURES & BENEFITS

The BZ-200 power pack switches connected loads on and off in response to Wattstopper low voltage occupancy sensors. It also provides up to 225mA at 24VDC to power the sensors. This device is RoHS-conforming.



- High-efficiency switching power supply
- Plenum rated
- Zero crossing for reliability and increased product life
- Load On/Off button to verify wiring
- UL listed controlled receptacles to meet energy code requirements
- Low voltage overcurrent protection
- 120-277VAC; 50/60Hz

### SPECIFICATIONS

#### ADDITIONAL INFORMATION

##### MODELS

Product Number: BZ-200, BZ-200-U

#### GENERAL INFO

Typical Applications: Low Voltage Power Pack

Product Series: BZ-200, BZ-200-U

Type: Power Pack

Special Features: Universal Voltage, Plenum rated, RoHS compliant

#### ASSEMBLY/INSTALLATION INFORMATION

Mounting Points: Integrated, External

#### LISTING AGENCIES/THIRD PARTY CERTIFICATIONS

RoHS: Yes

CUL Listing No: C22.2 No. 14-10

UL Listing No: UL244A, UL508

#### TECHNICAL INFORMATION

Amps: 20 Amps

Operating Temperature (Celsius): 0C-40C

Volts: 120, 240 , 277VAC, 50/60Hz