



### Catalog No. THQL32050

Description: CIRCUIT BRK 10KA QL 3P 240V 50A

UPC No 783164013047

Home > Circuit Breakers > Residential Circuit Breakers > Feeder Plug-in Circuit Breakers

Q line circuit breakers are one-inch wide per pole, compact, thermal-magnetic devices designed for residential and commercial applications. The QL breakers are plug-in versions of the Q Line used for connection to load centers and lighting panels. All Q Line circuit breakers feature Quick-make / Quick-break mechanisms, common trip bars, and easy to spot trip indication to ensure safety and reliability. Q Line breakers are available in 1, 2, and 3 pole versions, can be ordered with auxiliary contact and shunt trip accessories, and can be ordered for use in HID applications. 2050 Amps 50 A

#### Descriptors

Category	Feeder Plug-in Circuit Breakers
Product Line	Q-Line (Plug-In)
GO Schedule	R8

#### Specifications

Trip Style	Non-Interchangeable
Frame Type	Q-Line
Amperage	50 A
System Voltage	120 Vac 120/240 Vac 240 Vac
Poles	3
Trip Function	LI
Continuous Current Rated	Standard
120 Vac Interrupting Rating	10 KAIC
120/240 Vac Interrupting Rating	10 KAIC
240 Vac Interrupting Rating	10 KAIC
Suitable for Reverse Feed	Yes
Long Time	Fixed
Instantaneous	Fixed
Protective Relays	No
Current Metering	No
Special Markings	HACR
GSA Compliance	No

#### Classifications

UL File #	E11592
-----------	--------



## Publications

Title	Publication No.	Publication Type
<a href="#">PowerMark Gold* Load Centers, Q-Line Circuit Breakers and Accessories Guide</a> ptions list. Only available on-line.	DET1023	Application and Technical
<a href="#">Q-Line Plug-In MCCB, 100A Frame 1-, 2-, or 3- Pole, Drawing</a> 1-Page fully dimensioned outline drawing in .pdf format	455C872-SH1	Drawings-Outline and Dimensional

**Additional Documentation:** Visit our Publication Library to find technical documentation, time current curves, CSI Specifications and promotional literature.