

## Rigid Conduit


### Conduit Fittings and Accessories



**CILBA-1/2 / CILBA-2**




**CIELBA-2 1/2 / CIELBA-4**



**CITA-1/2 / CITA-4**



**CITBA-1/2 / CITBA-2**



Cat. No.	Trade Size (in.)	Dimensions (in.)		
		A	B	C
<b>Rigid Conduit Fittings - "LB" Type (Cast Aluminum)</b>				
<b>CILBA-1/2</b>	1/2	4-5/16	1-1/2	1-3/8
<b>CILBA-3/4</b>	3/4	4-15/16	1-7/8	1-9/16
<b>CILBA-1</b>	1	6-1/16	2-1/16	1-13/16
<b>CILBA-1-1/4</b>	1-1/4	7-7/8	2-15/16	2-1/2
<b>CILBA-1-1/2</b>	1-1/2	7-7/8	3-1/16	2-1/2
<b>CILBA-2</b>	2	10	3-3/4	3-3/16
<b>CIELBA-2-1/2</b>	2-1/2	13-3/8	5-1/4	5-1/8
<b>CIELBA-3</b>	3	13-3/8	5-1/4	5-1/8
<b>CIELBA-3-1/2</b>	3-1/2	16-1/8	6-11/16	5-7/8
<b>CIELBA-4</b>	4	16-1/8	6-11/16	5-7/8
<b>Rigid Conduit Fittings - "T" Type (Cast Aluminum)</b>				
<b>CITA-1/2</b>	1/2	4-7/8	1-3/8	2-1/16
<b>CITA-3/4</b>	3/4	5-9/16	1-3/4	2-1/8
<b>CITA-1</b>	1	6-1/2	2	2-1/2
<b>CITA-1-1/4</b>	1-1/4	8-11/16	2-5/8	3-1/2
<b>CITA-1-1/2</b>	1-1/2	8-11/16	3	3-9/16
<b>CITA-2</b>	2	10-7/8	3-1/4	4-3/16
<b>CITA-2-1/2</b>	2-1/2	12-5/8	6-3/8	5-3/4
<b>CITA-3</b>	3	12-5/8	6-3/8	5-3/4
<b>CITA-3-1/2</b>	3-1/2	14-7/8	7-1/8	6-3/4
<b>CITA-4</b>	4	14-7/8	7-1/8	6-3/4
<b>Rigid Conduit Fittings - "TB" Type (Cast Aluminum)</b>				
<b>CITBA-1/2</b>	1/2	4-3/8	1-3/8	1-3/8
<b>CITBA-3/4</b>	3/4	5-1/8	2-1/8	1-9/16
<b>CITBA-1</b>	1	6	2-1/2	1-13/16
<b>CITBA-1-1/4</b>	1-1/4	8-1/8	3-1/2	2-1/2
<b>CITBA-1-1/2</b>	1-1/2	8-1/8	3-1/2	2-1/2
<b>CITBA-2</b>	2	10-1/4	4-5/16	3-1/8

Gaskets and covers are included with all rigid conduit fittings  
 CILBA and CITA-1/2 to CITA-2 are also suitable for use with EMT conduit



**CIBC-1/2 / CIBC-2**



**CIG-1/2 / CIG-2**



Cat. No.	Trade Size (in.)
<b>Blank Covers for Aluminum Conduit Fittings (Stamped Aluminum)</b>	
<b>CIBC-1/2</b>	1/2
<b>CIBC-3/4</b>	3/4
<b>CIBC-1</b>	1
<b>CIBC-1-1/4</b>	1-1/4
<b>CIBC-2</b>	2

For 1-1/2, use CIBC-1-1/4



Cat. No.	Trade Size (in.)
<b>Gaskets for Aluminum Conduit Fittings (Neoprene)</b>	
<b>CIG-1/2</b>	1/2
<b>CIG-3/4</b>	3/4
<b>CIG-1</b>	1
<b>CIG-1-1/4</b>	1-1/4
<b>CIG-2</b>	2

For 1-1/2, use CIG-1-1/4