EMG 45-DIO 8E - Diode block

2950103

https://www.phoenixcontact.com/in/products/2950103

Please be informed that the data shown in this PDF document is generated from our Online Catalog. Please find the complete data in the user documentation. Our General Terms of Use for Downloads are valid.



Diode module, with 8 diodes, individually wired, diode type 1N 4007

Your advantages

- · Spark-suppression diodes for limiting surge voltages of inductive loads
- Electrical decoupling of messages in fault reporting systems

Commercial Data

Item number	2950103
Packing unit	5 pc
Minimum order quantity	1 pc
Sales Key	CK4
Product Key	CK4M11
Catalog Page	Page 266 (C-5-2019)
GTIN	4017918083953
Weight per Piece (including packing)	85.88 g
Weight per Piece (excluding packing)	85.88 g
Customs tariff number	85411000
Country of origin	DE

EMG 45-DIO 8E - Diode block

2950103

https://www.phoenixcontact.com/in/products/2950103



Technical Data

Product properties

	Product type	Diode module
Inp	out data	
I	Diode	
	Description of the input	8 diodes, individually wired
	Diode type	1 N 4007
	Max. operating voltage U _{max}	250 V AC
	Peak reverse voltage per diode	1300 V
	Reverse current per diode	5 μΑ
	Conducting state voltage per diode	approx. 0.8 V
	Conducting state current per diode	0.7 A (with single load)
		0.5 A (with simultaneous loads)

Connection data

Connection method	Screw connection
Stripping length	8 mm
Screw thread	M3
Conductor cross section rigid	0.2 mm ² 4 mm ²
Conductor cross section flexible	0.2 mm ² 2.5 mm ²
Conductor cross section AWG	24 12

Dimensions

Width	45 mm
Height	75 mm
Depth	55 mm

Environmental and real-life conditions

Ambient conditions		
Ambient t	emperature (operation)	-20 °C 50 °C
Ambient t	emperature (storage/transport)	-40 °C 70 °C

Approvals

Certificate	CE-compliant	
Note	and EN 61326	

Standards and regulations

	Standards/regulations	DIN EN 50178
--	-----------------------	--------------

EMG 45-DIO 8E - Diode block

2950103

https://www.phoenixcontact.com/in/products/2950103



Mounting type	DIN rail mounting
Assembly instructions	in rows with zero spacing
Mounting position	any

Phoenix Contact 2023 © - all rights reserved https://www.phoenixcontact.com

PHOENIX CONTACT (I) Pvt. Ltd. A-58/2, Okhla Industrial Area, Phase - II, New Delhi-110 020

+91.1275.71420 info@phoenixcontact.co.in