

GSA

Electronic/Glass Fuses

MIDGET, PC MOUNT & MINIATURE FUSES



GSA

- Ceramic body
- Time-delay
- 1/4" x 1-1/4"

1/2A through 8A,
250VAC, UL Listed

10, 12, 15A, 250V
UL Recognized

1/2A through 8A,
250VAC, CSA Certified

10, 12, 15A, 250V CSA Recognized

20A, 250VAC, 25 & 30A, 125VAC



STANDARD FUSE AMPERE RATINGS

| Catalog Number | Ampere Rating | Volts | I.R. |
|----------------|---------------|-------|------|
| GSA1/2 | 1/2A | 250V | 1 |
| GSA6/10 | 6/10A | 250V | 1 |
| GSA7/10 | 7/10A | 250V | 1 |
| GSA3/4 | 3/4A | 250V | 1 |
| GSA8/10 | 8/10A | 250V | 1 |
| GSA1 | 1A | 250V | 1 |
| GSA1-1/4 | 1-1/4A | 250V | 2 |
| GSA1-6/10 | 1-6/10A | 250V | 2 |
| GSA2 | 2A | 250V | 2 |
| GSA2-1/2 | 2-1/2A | 250V | 2 |
| GSA3 | 3A | 250V | 2 |
| GSA4 | 4A | 250V | 3 |
| GSA5 | 5A | 250V | 3 |
| GSA6 | 6A | 250V | 3 |
| GSA6-1/4 | 6-1/4A | 250V | 3 |
| GSA7 | 7A | 250V | 3 |
| GSA8 | 8A | 250V | 3 |
| GSA10 | 10A | 250V | 4 |
| GSA12 | 12A | 250V | 4 |
| GSA15 | 15A | 250V | 4 |
| GSA20 | 20A | 250V | 5 |
| GSA25 | 25A | 125V | 6 |
| GSA30 | 30A | 125V | 6 |

1. 250VAC @ 35A I.R./125VAC @ 10kA I.R.
2. 250VAC @ 100A I.R./125VAC @ 10kA I.R.
3. 250VAC @ 200A I.R./125VAC @ 10kA I.R.
4. 250VAC @ 750A I.R./125VAC @ 10kA I.R.
5. 250VAC @ 400A I.R./125VAC @ 10kA I.R.
6. 125VAC @ 400A I.R.