

# Eaton FAZ-B32/3N

Catalog Number: FAZ-B32/3N

Eaton FAZ supplementary protector,UL 1077 Industrial miniature circuit breaker - supplementary protector,Low levels of inrush current are expected,32 A,15 kAIC,Three-pole + neutral,3-5X /n,50-60 Hz,Standard terminals,B Curve



## General specifications

|   |  |
|---|--|
| <b>Product Name</b>                             | <b>Catalog Number</b>  |
| Eaton FAZ supplementary protector               | FAZ-B32/3N   |
| <b>EAN</b>                                      | <b>Product Length/Depth</b>  |
| 4015082789527                                   | 2.76 in  |
| <b>Product Height</b>                           | <b>Product Width</b>   |
| 3.25 in   | 3 in   |
| <b>Product Weight</b>                           | <b>Warranty</b>  |
| 1 lb  | 1 year   |
| <b>Certifications</b>                           | <b>Catalog Notes</b>   |
| CSA Std. C22.2 No.235<br>IEC 60947-2<br>UL 1077 | For applications that require protection due to potential wiring damage at low fault conditions. |

## Physical Attributes

### Number of poles

Three-pole + N

### Terminals

Standard

### Type

UL 1077 Industrial miniature circuit breaker - supplementary protector

## Performance Ratings

### Amperage Rating

32 A

### Circuit protection

B curve

### Frequency rating

50-60 Hz

### Interrupt rating

15 kAIC

### Trip Type

3-5X /n

## Miscellaneous

### Application

Suitable for applications where low levels of inrush current are expected

## Resources

### Brochures

[Industrial miniature circuit breakers UL 489](#)

### Catalogs

[Eaton's Volume 4—Circuit Protection](#)

### Specifications and datasheets

[Product Data Sheet - FAZ-B32/3N](#)

[Eaton Specification Sheet - FAZ-B32/3N](#)



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)