Eaton FH77

Catalog Number: FH77

Eaton A200/B100 heater, Used with A200 Starter Sizes 3 and 4, 3PH Only, A200 Heater, NEMA, Ambient 30.7-33.5A, Non-Comp 28.2-30.8A, Used with A200 Starter Sizes 3 and 4, 3PH Only, Type A and B, Thermal and Fast Trip

General specifications



Eaton A200/B100 heater UPC 786678670751 Product Height

1.3 in

Product Weight 0.06 lb

Certifications

CSA Certified

UL Listed

Product Name

FH77 Product Length/Depth 2.3 in Product Width

Catalog Number

1.9 in

Warranty

Eaton Selling Policy 25-000, one (1) year from the date of installation of the Product or eighteen (18) months from the date of shipment of the Product, whichever occurs first.

Catalog Notes

Select heater coils based on full load current(FLA) shown on motor nameplate. Heater coils are rated to protect 40 degree C rise and a service factor of 1.15, Single-Phase requires 2 heaters, Three-Phase Requires 3 heaters



defaultTaxonomyAttributeLabel

Special features Used with A200 Starter Sizes 3 & 4, 3-Phase Only

Туре

A200 Heater

Used with Used with A200 Starter Sizes 3 & 4, 3-Phase Only

Design

NEMA

Full load current range

Ambient 30.7-33.5 A, Non-Comp 28.2-30.8 A

Overload relay

Type A and B

Trip type

Thermal and fast trip



Eaton is a registered trademark.

Eaton.com All other trademarks are © 2024 Eaton. All Rights property of their respective Reserved. owners.



Eaton.com/socialmedia

Resources

Catalogs

Eaton's Volume 5-Motor Control and Protection

Installation instructions Instructions for A200, A210, A250 size 6, two- or three-pole nonreversing or reversing motor controllers

Specifications and datasheets Eaton Specification Sheet - FH77

