

# Eaton FAZ-C6/3-NA

Catalog Number: FAZ-C6/3-NA

Eaton FAZ branch protector, UL 489 Industrial miniature circuit breaker - supplementary protector, Medium levels of inrush current are expected, 6 A, 10 kAIC, 14 kAIC, Three-pole, 277/480 V, 5-10X /n, 50-60 Hz, Screw terminals, C Curve

## General specifications



Photo is representative

### Product Name

Eaton FAZ branch protector

### EAN

4015081021208

### Product Height

4.13 in

### Product Weight

1 lb

### Certifications

UL 489

CSA Std. C22.2 No. 235

### Catalog Number

FAZ-C6/3-NA

### Product Length/Depth

2.1 in

### Product Width

2.97 in

### Warranty

1 year

### Catalog Notes

Positioned for medium inrush startup currents to provide protection for small transformers and pilot devices.

## Physical Attributes

### Number of poles

Three-pole

### Terminals

Screw

### Type

UL 489 Industrial miniature circuit breaker - supplementary protector

## Performance Ratings

### Amperage Rating

6 A

### Circuit protection

C curve

### Frequency rating

50-60 Hz

### Interrupt rating

14 kAIC

10 kAIC

### Trip Type

5-10X /n

### Voltage rating

277/480V

## Miscellaneous

### Application

Suitable for applications where medium levels of inrush current are expected

## Resources

### Brochures

[Industrial miniature circuit breakers UL 489](#)

### Catalogs

[Eaton's Volume 4—Circuit Protection](#)

### Specifications and datasheets

[Product Data Sheet - FAZ-C6/3-NA](#)

[Eaton Specification Sheet - FAZ-C6/3-NA](#)



Eaton Corporation plc  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com  
© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



[Eaton.com/socialmedia](https://www.eaton.com/socialmedia)